

AD-A069 946

ILLINOIS UNIV AT CHICAGO CIRCLE DEPT OF MATHEMATICS
GENERALIZED YOUTEN DESIGNS: CONSTRUCTION AND TABLES.(U)

DEC 78 A ASH

F/G 12/1

AFOSR-76-3050

UNCLASSIFIED

| OF |
AD
A069946

AFOSR-TR-79-0686

NL



END
DATE
FILMED

- 7 - 79

DDC

A069946

AFOSR-TR- 79-0686


LEVEL



Edna/Clara

f. 4-4 = poor pages
4-5
4-6

THIS DOCUMENT IS DRAFT QUALITY TRANSMISSION.
THE COPY FURNISHED TO DDCI CONTAINED A
RELEVANT NUMBER OF FADING WHICH IS NOT
REPRODUCIBLE.



Approved for public release;
distribution unlimited.

39 06 11 060

DISCLAIMER NOTICE

**THIS DOCUMENT IS BEST QUALITY
PRACTICABLE. THE COPY FURNISHED
TO DDC CONTAINED A SIGNIFICANT
NUMBER OF PAGES WHICH DO NOT
REPRODUCE LEGIBLY.**

REPORT DOCUMENTATION PAGE		REF ID: A6510000
1. REPORT NUMBER AFOSR-TR-79-0686	2. GOVT ACCESSION NO.	3. DISTRIBUTION STATEMENT (DoD Only)
4. TITLE (and Subtitle) Generalized Youden Designs: Construction and Tables.	5. TIME OF REPORT (Month Year) Interim <i>rept.</i>	6. APPROVAL OR GRANT NUMBER AFOSR - 76-3050A
7. AUTHOR(s) Arlene Ash	8. SPONSORING ACTIVITY NUMBER 61102E 9769-05	9. CONTROLLING OFFICE NAME AND ADDRESS Air Force Office of Scientific Research (NM), Bolling AFB, Washington, D.C. 20332
10. PERFORMING ORGANIZATION NAME AND ADDRESS Department of Mathematics, University of Illinois at Chicago Circle, Box 4348, Chicago, Illinois 60680	11. PROGRAM ELEMENT, PROJECT, TASK AREA & WORK UNIT NUMBERS 112	12. REPORT DATE December 1978
13. MONITORING AGENCY NAME & ADDRESS (if different from Controlling Office) (12) 30P.	14. SECURITY CLASSIFICATION OF THIS REPORT Unclassified	15a. DISTRIBUTION STATEMENT (DoD Only) IC (DoD)
16. DISTRIBUTION STATEMENT (of the abstract entered in Block 20, if different from Report)		
17. SUPPLEMENTARY NOTES		
18. KEY WORDS (Continue on reverse side if necessary and identify by block number) Generalized Youden Designs, Balanced Block Designs, constructions, tables.		
19. ABSTRACT (Continue on reverse side if necessary and identify by block number) See attached page.		

Generalized Youden Designs
Construction and Tables¹

by

Arlene Ash
Department of Mathematics
University of Illinois at Chicago 409 950

Darrell

Accession For	
NTIS GRA&I	<input checked="" type="checkbox"/>
DDC TAB	<input type="checkbox"/>
Unannounced	<input type="checkbox"/>
Justification	
(CATA) 409 950	
By	
Distribution	
Available for Codes	
Dist	Avail and/or special
A	23
	p7c

¹ Research sponsored in part by Grant AFOSR-76-3050A.

20 06 11 060

SUMMARY

Generalized Youden Designs: Construction and Tables

by

Arlene Ash
University of Illinois at Chicago
and
Boston University

Generalized Youden Designs are generalizations of the class of two-way balanced block designs which include Latin squares and Youden squares. They are used for the same purposes and in the same way that these classical designs are used, and satisfy most of the most common criteria of design optimality.

We explicitly display or give detailed instructions for constructing all these designs within a practical range: when v , the number of treatments, is ≤ 25 ; and b_1 and b_2 , the dimensions of the design array, are each ≤ 50 .

•••••
•••

ABBREVIATED TITLE: Generalized Youden Designs.

FOOTNOTES

¹ This paper is part of the author's doctoral dissertation written at the University of Illinois at Chicago Circle. Research sponsored in part by Dartmouth College and Grant AFOSR-76-350A.

AMS 1970 subject classification. Primary 62K10; Secondary

Key words and phrases. Generalized Youden Designs, Balanced Block Designs, constructions, tables.

² GYD(v, b_1, b_2) and GYD(v', b'_1, b'_2) are in the same family if $v = v'$ and b_i is congruent to $b'_i \pmod{v}$, for $i = 1, 2$.

³ The rows of a $B_0 = GYD(22, 22, 7)$ would be a BIB(22, 22, 7) which cannot be constructed. See for example (Collens, 1976). A design with twice as many blocks, the smallest possible in this family, is listed instead.

⁴ No small design in this family exists, because of the non-existence of required BIB(15, 21, 5). See for example (Collens, 1976).

Generalized Youden Designs: Construction and Tables¹

by

Arlene Ash
University of Illinois at Chicago
and
Boston University

1. Introduction. A Generalized Youden Design (GYD) is a $b_1 \times b_2$ array on the treatments $\{1, \dots, v\}$ denoted $GYD(v, b_1, b_2)$, whose induced row and column designs satisfy certain technical conditions of balance. It is a natural generalization of several well-known highly balanced two-way design structures, such as the Latin square and the Youden square. Indeed, when $b_1 = v$ and $b_2 \leq v$, a $GYD(v, b_1, b_2)$ is exactly one of these designs. The GYD definition extends the collection of design settings in which two-way balance may be achieved, to include values of b_1 and b_2 which may be greater than v .

GYD's are used for comparing the performance of v treatments in the presence of two-way heterogeneity (in, respectively, b_1 and b_2 blocks) under the standard linear model with no interactions. For such purposes GYD's are optimal under several of the most common criteria of optimality [6]. This paper makes these statistically good designs available by listing (or giving explicit directions for constructing) those GYD's within a practical range: $v \leq 25$; $b_1, b_2 \leq 50$.

Associated with each design is a $v \times v$ matrix called the information matrix of the design (for the treatment means). Usually the goodness of a design is measured as some function of this matrix. Since non-isomorphic GYD's with the same parameters (v, b_1, b_2) have identical information matrices, we indicate only one possible construction for each parameter set where construction can be achieved. In the range specified there is only one

parameter set ($v = 25$, $b_1 = b_2 = 40$) where neither nonexistence of the GYD, nor any construction is known. We have, however, provided a 40×40 design, P18, the combined set of whose rows and columns form a balanced 80-block design. This makes it a Pseudo Youden Design (PYD) as defined by Cheng (1978) and gives it the same information matrix and optimality properties as the missing GYD.

Previous work by Seiden, Ruiz and Wu (1974, 1978) has provided explicit information for constructing many designs where v is a power of a prime. Theorems by Kiefer (1975) combined with lists of BIB's (Hanani, 1975 or Collens, 1976 for example) guarantee the existence of some other designs in our listing. Designs P18 and N3, 6, 10, 11, 12, 14 and 16 are apparently new.

Special acknowledgements are due to Ching-Shiu Cheng who pointed out that a BIB(25,80,15) could be substituted for two BIB(25,40,15)'s in making a PYD surrogate for GYD(25,40,40), and to Haim Hanani who provided the eighty block design which was used in making that construction. Thanks also to R. J. Collens who helped locate a needed BIB design from the updated listing he maintains on the University of Manitoba computer.

It still seems of some theoretical interest to know whether or not any GYD(25,40,40) exists.

2. Definitions and notation. Throughout this paper we will let

$$b_i = m_1 v + c_i, \quad 0 \leq c_i < v, \quad i = 1, 2.$$

Definition. A GYD(v, b_1, b_2) is a $b_1 \times b_2$ array with entries from $V = \{1, \dots, v\}$ such that

- (a) Every element of V occurs either m_1 or $m_1 + 1$ times in each column and either m_2 or $m_2 + 1$ times in each row; and
- (b) Every two distinct elements of V occur together in the same row the same number of times; and similarly for columns.

That is, the rows of a GYD form a so-called balanced block design,

$BBD(v, b=b_1, k=b_2)$; and the columns form a $BBD(v, b=b_2, k=b_1)$. The existence of BBD 's with the given parameters is equivalent to the existence of balanced incomplete block designs $BIB(v, b=b_1, k=c_2)$ and $BIB(v, b=b_2, k=c_1)$. Well-known parameter conditions are necessary for the existence of BIB 's, and consequently, for a fixed (v, c_1, c_2) , $GYD(v, b_1=m_1 v+c_1, b_2=m_2 v+c_2)$ can only exist when v divides $c_1 c_2$ and the b_i , in addition to being congruent to $c_i \bmod v$, satisfy these BIB -related conditions.

... .

... .

3. Construction. GYD construction is trivial when v divides both b_1 and b_2 , and essentially equivalent to the construction of a related BIB when v divides just one of b_1 or b_2 but not both. It is new and interesting when neither b_1 nor b_2 is a multiple of v . We distinguish these three design settings as, respectively, the doubly regular, (simply) regular and non-regular cases.

3.1 The doubly regular case. $\text{GYD}(v, b_1 = m_1 v, b_2 = m_2 v)$ can be constructed by juxtaposing any m_1 by m_2 collection of Latin squares. For example, let the (i,j) th entry of the array be v if $i + j \equiv 1 \pmod{v}$ and $(i + j - 1) \pmod{v}$ otherwise.

3.2 The (simply) regular case. Transposing the design if necessary we may assume that $c_1 = 0$. We may construct $\text{GYD}(v, b_1 = m_1 v, b_2 = m_2 v + c_2)$ by adjoining a doubly regular $\text{GYD}(v, m_1 v, m_2 v)$ to a regular $\text{GYD}(v, m_1 v, c_2)$.

For every v and $0 < c_2 < v$, there is a $b_0 = m_0 v$, such that if regular $B_1 = \text{GYD}(v, b_1 = m_1 v, c_2)$ exists then b_1 is a multiple of b_0 . If $B_0 = \text{GYD}(v, b_0, c_2)$ exists, then B_1 can be constructed by stacking b_1/b_0 copies of B_0 . $B_0 = B_0(v, c_2)$ is called a core design for the (v, c_2) -family of regular designs. We list instructions for finding B_0 :

3.2.1. If $c_2 = 1$, B_0 may be taken as the $(v \times 1)$ column array $[1, 2, \dots, v]'$, where the "prime" indicates transpose.

3.2.2. If $c_2 = 2$, B_0 will be a $v(v - 1) \times 2$ array for v even, and a $[v(v - 1)/2] \times 2$ array for odd v . In either case, construct the first column of B_0 by stacking copies of column vector $D = [1, 2, \dots, v]'$; and the second column by cycling the entries of D : i.e., first use $[2, 3, \dots, v, 1]'$, then $[3, 4, \dots, v, 1, 2]'$, etc. until the second column is filled. E.g. for $v = 5$ we get

1	2
2	3
3	4
4	5
5	1
1	3
2	4
3	5
4	1
5	2

$B_0 = B_0(5, 2) = GYD(5, 10, 2) =$

3.2.3. If $3 \leq c_2 \leq v/2$, the construction of B_0 is more complicated. For $v \leq 25$ and b_0 no bigger than 50, the design B_0 will be found in the regular design tables through the parameters (v, c_2) .

3.2.4. For $c_2 > v/2$, there is a three-step procedure. First, locate B'_0 , the core design for the $(v, c'_2 = v - c_2)$ family, as above. Then, construct $\text{comp}(B'_0)$, a row design complementary to B'_0 viewed only as a row design. That is, put $i \in \{1, \dots, v\}$ in the j^{th} row of the complementary design when i is not in the j^{th} row of the original. This new design is a $\text{BIB}(v, b_1, c_2)$, but the array may require rearrangement of the entries within rows so that the columns are also balanced. This can always be done (Agrawal, 1966), and for small designs it can be done rapidly by eye. Sometimes, if B'_0 has been constructed with a discernible column pattern this facilitates writing B_0


directly as a GYD. E.g., for GYD(7,21,18) we need GYD(7,21,4). Since $4 > 7/2$, we seek B'_0 , the core design for the ($v=7$, $c'_2=3$) family and find it, in section 4.2, as R2:

$$B'_0 = \begin{bmatrix} 1 & 2 & 4 \\ 2 & 3 & 5 \\ 3 & 4 & 6 \\ 4 & 5 & 7 \\ 5 & 6 & 1 \\ 6 & 7 & 2 \\ 7 & 1 & 3 \end{bmatrix}; \quad \text{comp}(B'_0) = \begin{bmatrix} 3 & 5 & 6 & 7 \\ 1 & 4 & 6 & 7 \\ 1 & 2 & 5 & 7 \\ 1 & 2 & 3 & 6 \\ 2 & 3 & 4 & 7 \\ 1 & 3 & 4 & 5 \\ 2 & 4 & 5 & 6 \end{bmatrix} \quad \text{or } \text{comp}(B'_0) = \begin{bmatrix} 3 & 5 & 6 & 7 \\ 4 & 6 & 7 & 1 \\ 5 & 7 & 1 & 2 \\ 6 & 1 & 2 & 3 \\ 7 & 2 & 3 & 4 \\ 1 & 3 & 4 & 5 \\ 2 & 4 & 5 & 6 \end{bmatrix}$$

A 21×14 doubly regular design, patched to a stack of three copies of the second version of $\text{comp}(B'_0)$, makes the desired GYD.

If "eyeball" methods fail to produce a rearrangement of the BIB which is column-balanced the appendix contains a definitive algorithm (called SHUFFLE) for turning a BIB with b a multiple of v into a GYD.

3.3. The Nonregular Case. GYD(v, b_1, b_2)'s exist for $b_i \equiv c_i \pmod{v}$, only when $v | c_1 c_2$. For such a triple (v, c_1, c_2) there are integers β_1, β_2, b_1^0 and b_2^0 such that any GYD(v, b_1, b_2) with $b_i \equiv c_i \pmod{v}$ has $b_1 = \beta_1 + b_1^0 s$ and $b_2 = \beta_2 + b_2^0 t$, for some $s, t \in \{0, 1, 2, \dots\}$. Here the β_i 's are minimal possible dimensions in the (v, c_1, c_2) -family; and the b_i^0 's are multiples of v for which BIB's in b_0^i blocks of size c_i can exist. $G_0 = \text{GYD}(v, \beta_1, \beta_2)$, if it exists, is called a core design for the family. If, further, regular designs $B_0^1 = \text{GYD}(v, b_1^0, c_2)$ and $B_0^2 = \text{GYD}(v, b_2^0, c_1)$ exist, then any GYD in this family can be constructed. One method is indicated in the diagram below, where the hatched regions are doubly regular designs.



Since nonregular designs cannot readily be assembled from the associated row and column designs, explicit constructions for the small core designs are given in 4.3. The parameters of the associated B_0^1 designs are indicated next to those of G_0 in the listing which precedes the constructions. Most of these, however, have too many blocks to be included in the tables of regular designs.

4. Guide to the tables. The tables contain the building blocks for GYD(v, b_1, b_2)'s with $v \leq 25$ and b_1, b_2 both ≤ 50 . We refer to such designs as "small". In order to determine whether or not a small GYD exists and to find its construction if it does, perform the numbered steps sequentially until they lead to an exit.

The exits are coded by

- \square GYD(v, b_1, b_2) does not exist, nor does any GYD in the same family² exist.
- \square GYD(v, b_1, b_2) with b_1 and b_2 both ≤ 50 does not exist although larger GYD's in the same family will.

\Rightarrow Proceed elsewhere, as directed.

The procedure is definitive for $v \leq 25$ and b_1, b_2 both ≤ 50 , although a Pseudo Youden Design (see the Introduction) has been offered instead of GYD(25, 40, 40) in the one place where we have not been able to achieve the more rigid construction. Even if b_1 or b_2 is bigger than 50, if $v \leq 25$ a construction may result if the GYD sought is in the same family as another design which is in the range of the tables. For $v > 25$, the procedure is only useful for determining when no design can exist.

4.1. Procedure for resolving a GYD(v, b_1, b_2) construction problem.

- 1) Compute c_i , the residue of $b_i \bmod v$, for $i = 1, 2$.
- 2) If $v \nmid c_1 c_2$, then no design exists. \square
- 3) If $c_1 = c_2 = 0$, the design construction is doubly regular and can be achieved. See 3.1. \Rightarrow

² GYD(v, b_1, b_2) and GYD(v', b'_1, b'_2) are in the same family if $v = v'$ and b_i is congruent to $b'_i \bmod v$, for $i = 1, 2$.

- 4) If necessary relabel b_1 and b_2 so that $c_1 \leq c_2$.
- 5) If $\frac{b_1 c_2}{v}$ and $\frac{b_1 c_2(c_2 - 1)}{v-1}$ are not both integers then no design exists. \square
- 6) If $c_1 = 0$, then the construction problem is regular. In this case do the following:
- If $c_2 = 1$ or 2 the design construction is trivial. See 3.2.1 or 3.2.2, respectively. \Rightarrow
 - Compute $h_2 = \text{g.c.d.}(v-1, c_2(c_2 - 1))$.
 - If $v(\frac{v-1}{h_2}) > 50$, no small design exists. \square
 - If $3 \leq c_2 \leq v/2$, look for the design in 4.2. \Rightarrow
 - If $c_2 > v/2$, see 3.2.4. \Rightarrow
- 7) If $\frac{b_2 c_1}{v}$ and $\frac{b_2 c_1(c_1 - 1)}{v-1}$ are not both integers, then no design exists. \square
- 8) Compute $g_i = \text{g.c.d.}(v, c_i)$ and $h_i = \text{g.c.d.}(v-1, c_i(c_i - 1))$, for $i = 1, 2$.
- 9) If either $\frac{v(v-1)}{g_2 h_2}$ or $\frac{v(v-1)}{g_1 h_1}$ is > 50 , no small design exists. \square
- 10) If $v = 25$ and $b_1 = b_2 = 40$, it is not known whether a GYD exists.
An equivalent design PYD(25, 40, 40) is listed in 4.3 as design P18. \Rightarrow
- 11) Look for the design in 4.3. \Rightarrow

4.2. Listings for regular designs. ($v \leq 25$; $c_1 = 0$; $c_2 \neq 0$).

For $\text{GYD}(v, b_1 = m_1 v, b_2 = m_2 v + c_2)$ to exist b_1 must be a multiple of

$$b_0 = b_0(v, c_2) = \frac{v(v-1)}{\text{g.c.d.}(v-1, c_2(c_2 - 1))},$$

where g.c.d. denotes greatest common divisor.

For $v \leq 25$, with $3 \leq c_2 \leq v/2$, if $b_0 \leq 50$, this table displays

$B_0 = GYD(v, b_0, c_2)$, from which G can be made by stacking b_1/b_0 copies of B_0 and adjoining an $m_1v \times m_2v$ doubly regular design (see 3.1). For one parameter set in this range, $v = 22$ and $c_2 = 7$, B_0 does not exist, and a design with $2b_0 = 44$ blocks is given instead.

For $v \leq 25$ and $c_2 > v/2$, B_0 can be constructed as the complement of a (v, c_2') -design, where $c_2' = v - c_2$. (See 3.2.3.)

For any v and $c_2 = 1$ or 2 , see sections 3.2.1 or 3.2.2 respectively.

Listing Name	Family (v, c_2)	Dimensions of B_0 $GYD(v, b_0, c_2)$	Listing Name	Family (v, c_2)	Dimensions of B_0 $GYD(v, b_0, c_2)$
R1	(6,3)	(6,30,3)	R13	(16,5)	(16,48,5)
R2	(7,3)	(7,7,3)	R14	(16,6)	(16,16,6)
R3	(9,3)	(9,36,3)	R15	(17,8)	(17,34,8)
R4	(9,4)	(9,18,4)	R16	(19,9)	(19,19,9)
R5	(10,3)	(10,30,3)	R17	(21,5)	(21,21,5)
R6	(10,4)	(10,30,4)	R18	(21,6)	(21,42,6)
R7	(11,5)	(11,11,5)	R19	(21,10)	(21,42,6)
R8	(13,3)	(13,26,3)	R20	(22,7)	(22,44,7) ³
R9	(13,4)	(13,13,4)	R21	(23,11)	(23,23,11)
R10	(13,5)	(13,39,5)	R22	(25,4)	(25,50,4)
R11	(13,6)	(13,26,6)	R23	(25,9)	(25,25,9)
R12	(15,7)	(15,15,7)	R24	(25,12)	(25,50,12)

Table 1: Small, core regular designs.

³ The rows of $B_0 = GYD(22,22,7)$ would be a BIB(22,22,7), which cannot be constructed. See for example (Collens, 1976). A design with twice as many blocks, the smallest possible in this family, is listed instead.

R1 IS A GYD(6 + 30 + 3)

	3	5		H4 IS A GYD(9 + 30 + 4)
5	2	6		2 4 6 8
5	3	6		4 5 7 9
4	1	4		1 3 8 9
5	4	2		2 3 4 7
4	6	3		1 6 7 9
4	1	5		1 2 5 8
6	1	2		3 6 7 8
3	2	3		1 4 5 6
3	3	4		2 3 5 7
2	5	6		1 3 5 7
6	5	3		1 2 3 6
6	4	1		2 5 6 7
2	4	1		5 6 8 9
3	6	1		3 4 5 8
4	1	5		3 4 6 9
2	6	1		1 2 4 9
3	2	1		2 7 8 9
3	2	4		1 4 7 8
1	5	3		
2	5	6		

R7 IS A GYD(31 + 33 + 5)

RS IS A GYD(10 + 30 + 3)

	3	2	9
5	4	2	
4	6	3	
5	4	1	
6	1	2	
2	3	1	
4	3	2	

RB IS A GYD(13 + 26 + 3)

	R2 IS A GYD(7 + 7 + 3)	R3 IS A GYD(9 + 36 + 3)
2	9 7 3	8 10 3
2	2 4 10	6 10 9
2	1 2 6	9 10 6
3	2 3 2	7 8 10
4	4 8 3	4 9 11
5	4 5 9	10 12 5
3	5 6 6	11 6 13
2	5 7 10	3 7 17
7	3 1 5	6 2 13
6	6 9 4	8 2 13
7	6 7 10	6 5 2
2	1 6 8	7 3 6
1	9 2 7	7 8 4
2	2 5 8	5 9 8
2	2 4 10	
2	1 2 6	
3	2 3 2	
4	4 8 3	
5	4 5 9	
3	5 6 6	
2	5 7 10	
7	3 1 5	
6	6 9 4	
8	8 10 3	
2	1 2 6	
4	4 8 3	
5	4 5 9	
3	5 6 6	
2	5 7 10	
7	3 1 5	
6	6 9 4	
8	8 10 3	
2	1 2 6	
4	4 8 3	
5	4 5 9	
3	5 6 6	
2	5 7 10	
7	3 1 5	
6	6 9 4	
8	8 10 3	
2	1 2 6	
4	4 8 3	
5	4 5 9	
3	5 6 6	
2	5 7 10	
7	3 1 5	
6	6 9 4	
8	8 10 3	
2	1 2 6	
4	4 8 3	
5	4 5 9	
3	5 6 6	
2	5 7 10	
7	3 1 5	
6	6 9 4	
8	8 10 3	
2	1 2 6	
4	4 8 3	
5	4 5 9	
3	5 6 6	
2	5 7 10	
7	3 1 5	
6	6 9 4	
8	8 10 3	
2	1 2 6	
4	4 8 3	
5	4 5 9	
3	5 6 6	
2	5 7 10	
7	3 1 5	
6	6 9 4	
8	8 10 3	
2	1 2 6	
4	4 8 3	
5	4 5 9	
3	5 6 6	
2	5 7 10	
7	3 1 5	
6	6 9 4	
8	8 10 3	
2	1 2 6	
4	4 8 3	
5	4 5 9	
3	5 6 6	
2	5 7 10	
7	3 1 5	
6	6 9 4	
8	8 10 3	
2	1 2 6	
4	4 8 3	
5	4 5 9	
3	5 6 6	
2	5 7 10	
7	3 1 5	
6	6 9 4	
8	8 10 3	
2	1 2 6	
4	4 8 3	
5	4 5 9	
3	5 6 6	
2	5 7 10	
7	3 1 5	
6	6 9 4	
8	8 10 3	
2	1 2 6	
4	4 8 3	
5	4 5 9	
3	5 6 6	
2	5 7 10	
7	3 1 5	
6	6 9 4	
8	8 10 3	
2	1 2 6	
4	4 8 3	
5	4 5 9	
3	5 6 6	
2	5 7 10	
7	3 1 5	
6	6 9 4	
8	8 10 3	
2	1 2 6	
4	4 8 3	
5	4 5 9	
3	5 6 6	
2	5 7 10	
7	3 1 5	
6	6 9 4	
8	8 10 3	
2	1 2 6	
4	4 8 3	
5	4 5 9	
3	5 6 6	
2	5 7 10	
7	3 1 5	
6	6 9 4	
8	8 10 3	
2	1 2 6	
4	4 8 3	
5	4 5 9	
3	5 6 6	
2	5 7 10	
7	3 1 5	
6	6 9 4	
8	8 10 3	
2	1 2 6	
4	4 8 3	
5	4 5 9	
3	5 6 6	
2	5 7 10	
7	3 1 5	
6	6 9 4	
8	8 10 3	
2	1 2 6	
4	4 8 3	
5	4 5 9	
3	5 6 6	
2	5 7 10	
7	3 1 5	
6	6 9 4	
8	8 10 3	
2	1 2 6	
4	4 8 3	
5	4 5 9	
3	5 6 6	
2	5 7 10	
7	3 1 5	
6	6 9 4	
8	8 10 3	
2	1 2 6	
4	4 8 3	
5	4 5 9	
3	5 6 6	
2	5 7 10	
7	3 1 5	
6	6 9 4	
8	8 10 3	
2	1 2 6	
4	4 8 3	
5	4 5 9	
3	5 6 6	
2	5 7 10	
7	3 1 5	
6	6 9 4	
8	8 10 3	
2	1 2 6	
4	4 8 3	
5	4 5 9	
3	5 6 6	
2	5 7 10	
7	3 1 5	
6	6 9 4	
8	8 10 3	
2	1 2 6	
4	4 8 3	
5	4 5 9	
3	5 6 6	
2	5 7 10	
7	3 1 5	
6	6 9 4	
8	8 10 3	
2	1 2 6	
4	4 8 3	
5	4 5 9	
3	5 6 6	
2	5 7 10	
7	3 1 5	
6	6 9 4	
8	8 10 3	
2	1 2 6	
4	4 8 3	
5	4 5 9	
3	5 6 6	
2	5 7 10	
7	3 1 5	
6	6 9 4	
8	8 10 3	
2	1 2 6	
4	4 8 3	
5	4 5 9	
3	5 6 6	
2	5 7 10	
7	3 1 5	
6	6 9 4	
8	8 10 3	
2	1 2 6	
4	4 8 3	
5	4 5 9	
3	5 6 6	
2	5 7 10	
7	3 1 5	
6	6 9 4	
8	8 10 3	
2	1 2 6	
4	4 8 3	
5	4 5 9	
3	5 6 6	
2	5 7 10	
7	3 1 5	
6	6 9 4	
8	8 10 3	
2	1 2 6	
4	4 8 3	
5	4 5 9	
3	5 6 6	
2	5 7 10	
7	3 1 5	
6	6 9 4	
8	8 10 3	
2	1 2 6	
4	4 8 3	
5	4 5 9	
3	5 6 6	
2	5 7 10	
7	3 1 5	
6	6 9 4	
8	8 10 3	
2	1 2 6	
4	4 8 3	
5	4 5 9	
3	5 6 6	
2	5 7 10	
7	3 1 5	
6	6 9 4	
8	8 10 3	
2	1 2 6	
4	4 8 3	
5	4 5 9	
3	5 6 6	
2	5 7 10	
7	3 1 5	
6	6 9 4	
8	8 10 3	
2	1 2 6	
4	4 8 3	
5	4 5 9	
3	5 6 6	
2	5 7 10	
7	3 1 5	
6	6 9 4	
8	8 10 3	
2	1 2 6	
4	4 8 3	
5	4 5 9	
3	5 6 6	
2	5 7 10	
7	3 1 5	
6	6 9 4	
8	8 10 3	
2	1 2 6	
4	4 8 3	
5	4 5 9	
3	5 6 6	
2	5 7 10	
7	3 1 5	
6	6 9 4	
8	8 10 3	
2	1 2 6	
4	4 8 3	
5	4 5 9	
3	5 6 6	
2	5 7 10	
7	3 1 5	
6	6 9 4	
8	8 10 3	
2	1 2 6	
4	4 8 3	
5	4 5 9	
3	5 6 6	
2	5 7 10	
7	3 1 5	
6	6 9 4	
8	8 10 3	
2	1 2 6	
4	4 8 3	
5	4 5 9	
3	5 6 6	
2	5 7 10	
7	3 1 5	
6	6 9 4	
8	8 10 3	
2	1 2 6	
4	4 8 3	
5	4 5 9	
3	5 6 6	
2	5 7 10	
7	3 1 5	
6	6 9 4	
8	8 10 3	
2	1 2 6	
4	4 8 3	
5	4 5 9	
3	5 6 6	
2	5 7 10	
7	3 1 5	
6	6 9 4	
8	8 10 3	
2	1 2 6	
4	4 8 3	
5	4 5 9	
3	5 6 6	
2	5 7 10	
7	3 1 5	
6	6 9 4	
8	8 10 3	
2	1 2 6	
4	4 8 3	
5	4 5 9	
3	5 6 6	
2	5 7 10	
7	3 1 5	
6	6 9 4	
8	8 10 3	
2	1 2 6	
4	4 8 3	
5	4 5 9	
3	5 6 6	
2	5 7 10	
7	3 1 5	
6	6 9 4	
8	8 10 3	
2	1 2 6	
4	4 8 3	
5	4 5 9	
3	5 6 6	
2	5 7 10	
7	3 1 5	
6	6 9 4	
8	8 10 3	
2	1 2 6	
4	4 8 3	
5	4 5 9	
3	5 6 6	
2	5 7 10	
7	3 1 5	
6	6 9 4	
8	8 10 3	
2	1 2 6	
4	4 8 3	
5	4 5 9	
3	5 6 6	
2	5 7 10	
7	3 1 5	</

R12 15 A GYDE 15 + 15 + 7)

1	13	11	10	12	14	15
7	15	2	14	9	8	13
6	3	8	7	15	12	11
4	10	12	6	14	9	7
5	7	10	8	13	11	6
14	4	6	15	3	13	5
2	11	7	4	5	15	12
3	12	14	5	8	2	10
13	9	3	2	11	10	4
15	5	9	1	10	4	8
11	14	5	3	7	1	9
12	8	1	13	4	7	3
9	6	13	12	1	5	2
8	1	4	11	2	6	14
10	2	15	7	6	3	1

R13 15 A GYDE 17 + 34 + 8)

1	4	9	16	8	2	15	13
2	5	10	17	9	3	16	14
3	6	11	1	10	4	17	15
4	7	12	2	11	5	1	16
5	8	13	3	12	6	2	17
6	9	14	4	13	7	3	1
7	10	15	5	14	8	4	2
8	11	16	6	15	9	5	3
9	12	17	7	16	10	6	4
10	13	1	8	17	11	7	5
11	14	2	9	1	12	8	6
12	15	3	10	2	13	9	7
13	16	4	11	3	14	10	8
14	17	5	12	4	15	11	9
15	1	6	13	5	16	12	10
16	2	7	14	6	17	13	11
17	3	8	15	7	1	14	12

R18 15 A GYDE 21 + 42 + 6) 4

7	5	8	11	16	17
1	6	9	12	17	18
2	7	10	13	18	19
3	1	11	14	19	20
4	2	12	8	15	21
5	3	13	9	10	11
6	4	14	1	12	13
7	5	15	2	13	14
8	6	16	3	11	12
9	7	17	4	10	11
10	8	18	5	13	14
11	9	19	6	14	15
12	10	20	7	15	16
13	11	21	8	16	17
14	12	22	9	17	18
15	13	23	10	18	19
16	14	24	11	19	20
17	15	25	12	20	21
18	16	26	13	21	22
19	17	27	14	22	23
20	18	28	15	23	24
21	19	29	16	24	25
22	20	30	17	25	26
23	21	31	18	26	27
24	22	32	19	27	28
25	23	33	20	28	29
26	24	34	21	29	30
27	25	35	22	30	31
28	26	36	23	31	32
29	27	37	24	32	33
30	28	38	25	33	34

R13 15 A GYDE 16 + 48 + 5)

5	3	6	9	12
16	4	8	2	1
12	10	11	7	15
3	5	14	13	16
9	14	5	15	7
2	11	10	16	13
7	8	4	12	9
13	6	3	1	2
4	16	7	11	5
3	15	13	14	10
5	1	9	6	4
10	12	2	8	3
11	2	12	4	6
14	9	1	3	8
6	13	15	5	11
8	7	16	10	14
1	4	7	10	13

R14 15 A GYDE 19 + 19 + 9)

12	3	13	5	7
16	5	9	3	2
15	10	2	4	9
13	11	12	8	1
7	14	1	6	12
2	6	15	14	16
9	8	16	11	15
30	15	6	1	8
5	16	8	12	6
3	12	11	16	14
4	1	14	15	11
8	9	5	13	10
6	2	10	7	5
34	7	4	2	3
33	13	3	9	4
2	5	8	11	14
9	10	6	14	11
13	4	14	6	8
7	3	11	8	6
16	6	10	4	3
15	8	5	3	4
3	11	3	5	10
12	14	4	10	5
14	12	13	9	2
11	3	7	2	9
8	15	2	7	13
6	16	9	13	7
3	16	5	9	13
3	7	1	15	16
4	13	12	16	15
10	9	16	12	1
5	2	15	1	12

R17 15 A GYDE 21 + '21 + 5)

5	2	9	3	4	13
14	1	6	4	3	10
11	15	4	2	1	7
8	12	3	1	2	16
9	6	8	7	13	1
2	5	10	8	7	14
25	3	5	6	8	17
12	16	7	5	6	4
13	10	1	11	12	5
6	9	14	12	11	2
3	7	15	10	9	12
16	4	11	9	10	8
1	14	16	15	5	9
10	13	2	16	15	6
7	11	13	14	16	3
4	8	12	13	14	15

R19 15 A GYDE 21 + 42 + 10)

15	18	1	2	3	5	8	9	10
16	17	19	2	3	4	6	7	5
17	18	20	3	4	5	7	8	6
18	19	21	4	5	6	8	9	7
19	20	21	5	6	7	9	10	8
20	21	22	6	7	8	10	11	9
21	22	23	7	8	9	12	13	11
22	23	24	8	9	10	13	14	12
23	24	25	9	10	11	14	15	13
24	25	26	10	11	12	15	16	14
25	26	27	11	12	13	16	17	15
26	27	28	12	13	14	17	18	16
27	28	29	13	14	15	18	19	17
28	29	30	14	15	16	19	20	18
29	30	31	15	16	17	20	21	19
30	31	32	16	17	18	21	22	20
31	32	33	17	18	19	22	23	21
32	33	34	18	19	20	23	24	22
33	34	35	19	20	21	24	25	23
34	35	36	20	21	22	25	26	24
35	36	37	21	22	23	26	27	25
36	37	38	22	23	24	27	28	26
37	38	39	23	24	25	28	29	27
38	39	40	24	25	26	29	30	28
39	40	41	25	26	27	30	31	29
40	41	42	26	27	28	31	32	30
41	42	43	27	28	29	32	33	31
42	43	44	28	29	30	33	34	32
43	44	45	29	30	31	34	35	33
44	45	46	30	31	32	35	36	34
45	46	47	31	32	33	36	37	35
46	47	48	32	33	34	37	38	36
47	48	49	33	34	35	38	39	37
48	49	50	34	35	36	39	40	38
49	50	51	35	36	37	40	41	39
50	51	52	36	37	38	41	42	40
51	52	53	37	38	39	42	43	41
52	53	54	38	39	40	43	44	42
53	54	55	39	40	41	44	45	43
54	55	56	40	41	42	45	46	44
55	56	57	41	42	43	46	47	45
56	57	58	42	43	44	47	48	46
57	58	59	43	44	45	48	49	47
58	59	60	44	45	46	49	50	48
59	60	61	45	46	47	50	51	49
60	61	62	46	47	48	51	52	50
61	62	63	47	48	49	52	53	51
62	63	64	48	49	50	53	54	52
63	64	65	49	50	51	54	55	53
64	65	66	50	51	52	55	56	54
65	66	67	51	52	53	56	57	55
66	67	68	52	53	54	57	58	56
67	68	69	53	54	55	58	59	57
68	69	70	54	55	56	59	60	58
69	70	71	55	56	57	60	61	59

R220 15 A GYR(22 + 44 + 7)

22	1	2	4	32	15	20
1	2	3	7	13	16	21
2	3	4	8	14	17	22
3	4	5	9	15	18	1
4	5	6	10	16	19	2
5	6	7	11	17	20	3
6	7	8	12	18	21	4
7	8	9	13	19	22	5
8	9	10	14	20	1	6
9	10	11	15	21	2	7
10	11	12	16	22	3	8
11	12	13	17	1	4	9
12	13	14	18	2	5	10
13	14	15	19	3	6	11
14	15	16	20	4	7	12
15	16	17	21	5	8	13
16	17	18	22	6	9	14
17	18	19	1	7	10	15
18	19	20	2	8	11	16
19	20	21	3	9	12	17
20	21	22	4	10	13	18
21	22	1	5	11	14	19
22	2	3	4	10	15	19
1	3	4	5	11	16	20
2	4	5	6	12	17	21
3	5	6	7	13	18	22
4	6	7	8	14	19	1
5	7	8	9	15	20	2
6	8	9	10	16	21	3
7	9	10	11	17	22	4
8	10	11	12	18	1	5
9	11	12	13	19	2	6
10	12	13	14	20	3	7
11	13	14	15	21	4	8
12	14	15	16	22	5	9
13	15	16	17	1	6	10
14	16	17	18	2	7	11
15	17	18	19	3	8	12
16	18	19	20	4	9	13
17	19	20	21	5	10	14
18	20	21	22	6	11	15
19	21	22	1	7	12	16
20	22	1	2	8	13	17
21	3	2	3	9	14	18

R22 15 A GYR(25 + 50 + 4)

25	24	8	16
24	6	4	20
6	10	11	7
18	12	9	21
12	25	19	23
1	17	22	11-
17	14	3	9
14	15	2	19
15	10	5	8
10	1	13	4
7	21	24	2
21	23	6	5
23	16	18	13
16	20	12	22
20	7	2	15
19	8	17	18
18	4	14	12
4	11	15	25
11	9	10	24
9	19	1	6
13	22	21	15
22	3	23	10
3	2	16	1
2	5	20	17
5	13	7	14
25	2	10	18
24	5	1	12
6	13	17	25
18	22	14	24-
12	3	15	6
1	18	20	15
17	12	7	10
14	25	21	1
15	24	23	17
10	6	16	14
7	15	9	16
21	10	19	26
23	1	8	7
16	25	6	11
20	24	18	9
19	14	10	13
20	14	11	23
9	6	16	11
9	23	2	4
11	21	3	8
9	23	2	4
13	11	12	2
9	25	5	5
3	19	24	13
2	8	6	22
5	4	18	3

R24 15 A GYR(25 + 50 + 12)

2	4	6	8	10	12	14	16	18	20	22	24
5	11	18	4	3	25	15	20	12	7	3	6
3	9	12	17	22	11-	13	17	24	10	7	21
13	9	14	15	2	19	1	14	21	4	11	18
22	19	25	5	2	20	21	6	17	1	13	22
1	2	3	23	20	25	16	15	7	2	22	1
11	13	15	17	19	21	19	9	22	10	14	8
17	2	3	23	20	25	16	15	7	2	22	4
14	5	7	23	20	25	16	15	7	2	22	3
15	13	15	17	19	21	19	9	22	10	14	8
16	14	16	18	20	22	17	15	7	2	22	2
17	12	14	16	18	20	17	15	7	2	22	1
18	10	12	14	16	18	17	15	7	2	22	0
19	8	10	12	14	16	15	13	11	9	11	6
20	6	8	10	12	14	13	11	9	7	9	5
21	4	6	8	10	12	14	13	11	9	11	7
22	2	4	6	8	10	12	14	13	11	9	11
23	1	3	5	7	9	11	13	15	17	19	21
24	0	2	4	6	8	10	12	14	16	18	20
25	5	7	9	11	13	15	17	19	21	23	25

R21 15 A GYR(23 + 23 + 11)

1	4	9	16	2	13	3	18	12	18	6
2	5	10	17	3	14	4	19	13	19	7
3	6	11	18	4	15	5	20	14	210	8
4	7	12	19	5	16	6	21	15	211	9
5	8	13	20	6	17	7	22	16	212	10
6	9	14	21	7	18	8	23	17	213	11
7	10	15	22	8	19	9	1	18	214	12
8	11	16	23	9	20	10	2	19	215	13
9	12	17	1	10	21	11	3	20	216	14
10	13	18	2	11	22	12	4	21	217	15
11	14	19	3	12	23	13	5	22	218	16
12	15	20	4	13	1	14	6	23	219	17
13	16	21	5	14	2	15	7	1	220	18
14	17	22	6	15	3	16	8	2	221	19
15	18	23	7	16	4	17	9	3	222	20
16	19	1	8	17	5	18	10	4	223	21
17	20	2	9	18	6	19	11	5	224	22
18	21	3	10	19	7	20	12	6	225	23
19	22	4	11	20	8	21	13	7	226	24
20	23	5	12	21	9	22	14	8	227	25
21	1	6	13	22	10	23	15	9	228	26
22	2	7	14	23	11	1	16	10	6	229
23	3	8	15	1	12	2	17	11	7	5

R23 15 A GYR(25 + 25 + 9)

1	2	3	4	5	6	7	8	9
2	8	10	5	19	16	14	12	21
3	7	15	13	10	5	22	16	25
4	13	24	3	8	10	21	23	18
5	4	25	21	23	17	19	15	6
6	17	20	10	14	13	9	3	19
7	18	13	12	4	1	17	19	16
8	20	18	11	17	2	13	5	15
9	25	16	23	2	14	11	4	13
10	12	23	25	7	18	20	6	2
11	19	21	24	13	7	6	2	22
12	22	17	2	24	15	4	9	10
13	15	6	14	25	12	8	1	24
14	24	5	17	12	11	3	7	23
15	21	12	6	11	9	16	18	3
16	9	7	15	20	19	23	24	8
17	1	2	16	21	3	24	25	20
18	3	19	1	15	23	2	22	14
19	11	4	8	3	22	25	20	12
20	10	14	7	1	4	15	21	11
21	14	8	9	22	25	18	23	5
22	23	1	20	9	21	12	13	5
23	16	11	22	6	8	1	10	17
24	6	22	18	16	20	5	14	4
25	5	9	19	18	24	10	11	1

4.3. Listings for nonregular designs ($v \leq 25$; $0 \neq c_1 \leq c_2$).

For GYD($v, b_1 = m_1v + c_1, b_2 = m_2v + c_2$) to exist v must divide c_1c_2 , and the b_i 's, in addition to satisfying congruency to $c_i \pmod{v}$, must have, for $i = 1, 2$ and $j = 2, 1$ respectively, b_i is a multiple of

$$b_i \equiv \frac{v}{\text{g.c.d.}(v, c_j)} \cdot \frac{(v-1)}{\text{g.c.d.}(v-1, c_j(c_j-1))},$$

where g.c.d. denotes greatest common divisor.

Core designs $G_0 = \text{GYD}(v, \beta_1, \beta_2)$ in this family are listed below. whenever these smallest possible constructions have $v \leq 25$, β_1 and $\beta_2 \leq 50$. Larger designs in the same family can be constructed by making a patchwork of regular designs, using $B_1^0 = \text{GYD}(v, b_1^0, c_2)$ and $B_2^0 = \text{GYD}(v, b_2^0, c_1)$ in the construction. (See 3.3.)

Table 2:
Small, core nonregular designs.

Listing Name	(v, c_1, c_2) -family	Core Design, G_0 (v, β_1, β_2)	Associated Designs $B_1^0 = (v, b_1^0, c_2)$	$B_2^0 = (v, b_2^0, c_1)$
N1	(4, 2, 2)	(4, 6, 6)	(4, 12, 2)	(4, 12, 2)
N2	(6, 2, 3)	(6, 20, 15)	(6, 30, 3)	(6, 30, 2)
N3	(6, 3, 4)	(6, 15, 10)	(6, 30, 4)	(6, 30, 3)
N4	(8, 2, 4)	(8, 42, 28)	(8, 56, 4)	(8, 56, 2)
N5	(8, 4, 4)	(8, 28, 28)	(8, 56, 4)	(8, 56, 4)
N6	(8, 4, 6)	(8, 28, 14)	(8, 56, 6)	(8, 56, 4)
N7	(9, 3, 3)	(9, 12, 12)	(9, 36, 3)	(9, 36, 3)
N8	(9, 3, 6)	(9, 12, 24)	(9, 36, 6)	(9, 36, 3)
N9	(9, 6, 6)	(9, 24, 24)	(9, 36, 6)	(9, 36, 6)
N10	(10, 5, 6)	(10, 15, 36)	(10, 30, 6)	(10, 90, 5)
N11	(10, 5, 8)	(10, 45, 18)	(10, 90, 8)	(10, 90, 5)
N12	(12, 8, 9)	(12, 44, 33)	(12, 132, 9)	(12, 132, 8)
- ⁴	(15, 5, 6)	(15, 35, 21)	(15, 105, 6)	(15, 105, 5)
N14	(15, 5, 12)	(15, 35, 42)	(15, 105, 12)	(15, 105, 5)
N15	(16, 4, 4)	(16, 20, 20)	(16, 80, 4)	(16, 80, 4)
N16	(21, 9, 14)	(21, 30, 35)	(21, 210, 14)	(21, 150, 9)
N17	(25, 5, 5)	(25, 30, 30)	(25, 150, 5)	(25, 150, 5)
P18 ⁵	(25, 40, 40)	(25, 40, 40)	(25, 300, 15)	(25, 300, 15)

⁴ No small design in this family exists, because of the non-existence of required BIB(15, 21, 5). See for example (Collens, 1976).

⁵ The construction listed is a Pseudo Youden Design. See the Introduction.

N1 IS A GYDE 4 + 6 + 6)

	2	4
Latin square	3	2
of order 4	4	1
	1	3
3	2	4
4	2	1
3	3	2

N2 IS A GYDE 6 + 15 + 20)

	5	1
	5	6
	4	1
	4	6
	3	5
	3	4
	3	1
	3	6
	2	6
	2	5
	2	4
	2	1
2	3	1
5	4	5
3	2	3
1	2	6
4	6	5
5	2	3
3	2	3
2	3	2
3	2	6
1	5	1
5	1	4
2	4	2
3	1	5
4	2	3
6	5	3
1	5	4
2	4	1
3	3	6
4	2	5
5	1	3
6	3	2
7	6	4
8	5	1
9	4	3
10	3	2
11	2	1
12	1	6
13	5	4
14	4	3
15	3	2
16	2	1
17	1	6
18	5	4
19	4	3
20	3	2
21	2	1
22	1	6
23	5	4
24	4	3
25	3	2
26	2	1
27	1	6
28	5	4
29	4	3
30	3	2
31	2	1
32	1	6
33	5	4
34	4	3
35	3	2
36	2	1
37	1	6
38	5	4
39	4	3
40	3	2
41	2	1
42	1	6
43	5	4
44	4	3
45	3	2
46	2	1
47	1	6
48	5	4
49	4	3
50	3	2
51	2	1
52	1	6
53	5	4
54	4	3
55	3	2
56	2	1
57	1	6
58	5	4
59	4	3
60	3	2
61	2	1
62	1	6
63	5	4
64	4	3
65	3	2
66	2	1
67	1	6
68	5	4
69	4	3
70	3	2
71	2	1
72	1	6
73	5	4
74	4	3
75	3	2
76	2	1
77	1	6
78	5	4
79	4	3
80	3	2
81	2	1
82	1	6
83	5	4
84	4	3
85	3	2
86	2	1
87	1	6
88	5	4
89	4	3
90	3	2
91	2	1
92	1	6
93	5	4
94	4	3
95	3	2
96	2	1
97	1	6
98	5	4
99	4	3
100	3	2
101	2	1
102	1	6
103	5	4
104	4	3
105	3	2
106	2	1
107	1	6
108	5	4
109	4	3
110	3	2
111	2	1
112	1	6
113	5	4
114	4	3
115	3	2
116	2	1
117	1	6
118	5	4
119	4	3
120	3	2
121	2	1
122	1	6
123	5	4
124	4	3
125	3	2
126	2	1
127	1	6
128	5	4
129	4	3
130	3	2
131	2	1
132	1	6
133	5	4
134	4	3
135	3	2
136	2	1
137	1	6
138	5	4
139	4	3
140	3	2
141	2	1
142	1	6
143	5	4
144	4	3
145	3	2
146	2	1
147	1	6
148	5	4
149	4	3
150	3	2
151	2	1
152	1	6
153	5	4
154	4	3
155	3	2
156	2	1
157	1	6
158	5	4
159	4	3
160	3	2
161	2	1
162	1	6
163	5	4
164	4	3
165	3	2
166	2	1
167	1	6
168	5	4
169	4	3
170	3	2
171	2	1
172	1	6
173	5	4
174	4	3
175	3	2
176	2	1
177	1	6
178	5	4
179	4	3
180	3	2
181	2	1
182	1	6
183	5	4
184	4	3
185	3	2
186	2	1
187	1	6
188	5	4
189	4	3
190	3	2
191	2	1
192	1	6
193	5	4
194	4	3
195	3	2
196	2	1
197	1	6
198	5	4
199	4	3
200	3	2
201	2	1
202	1	6
203	5	4
204	4	3
205	3	2
206	2	1
207	1	6
208	5	4
209	4	3
210	3	2
211	2	1
212	1	6
213	5	4
214	4	3
215	3	2
216	2	1
217	1	6
218	5	4
219	4	3
220	3	2
221	2	1
222	1	6
223	5	4
224	4	3
225	3	2
226	2	1
227	1	6
228	5	4
229	4	3
230	3	2
231	2	1
232	1	6
233	5	4
234	4	3
235	3	2
236	2	1
237	1	6
238	5	4
239	4	3
240	3	2
241	2	1
242	1	6
243	5	4
244	4	3
245	3	2
246	2	1
247	1	6
248	5	4
249	4	3
250	3	2
251	2	1
252	1	6
253	5	4
254	4	3
255	3	2
256	2	1
257	1	6
258	5	4
259	4	3
260	3	2
261	2	1
262	1	6
263	5	4
264	4	3
265	3	2
266	2	1
267	1	6
268	5	4
269	4	3
270	3	2
271	2	1
272	1	6
273	5	4
274	4	3
275	3	2
276	2	1
277	1	6
278	5	4
279	4	3
280	3	2
281	2	1
282	1	6
283	5	4
284	4	3
285	3	2
286	2	1
287	1	6
288	5	4
289	4	3
290	3	2
291	2	1
292	1	6
293	5	4
294	4	3
295	3	2
296	2	1
297	1	6
298	5	4
299	4	3
300	3	2
301	2	1
302	1	6
303	5	4
304	4	3
305	3	2
306	2	1
307	1	6
308	5	4
309	4	3
310	3	2
311	2	1
312	1	6
313	5	4
314	4	3
315	3	2
316	2	1
317	1	6
318	5	4
319	4	3
320	3	2
321	2	1
322	1	6
323	5	4
324	4	3
325	3	2
326	2	1
327	1	6
328	5	4
329	4	3
330	3	2
331	2	1
332	1	6
333	5	4
334	4	3
335	3	2
336	2	1
337	1	6
338	5	4
339	4	3
340	3	2
341	2	1
342	1	6
343	5	4
344	4	3
345	3	2
346	2	1
347	1	6
348	5	4
349	4	3
350	3	2
351	2	1
352	1	6
353	5	4
354	4	3
355	3	2
356	2	1
357	1	6
358	5	4
359	4	3
360	3	2
361	2	1
362	1	6
363	5	4
364	4	3
365	3	2
366	2	1
367	1	6
368	5	4
369	4	3
370	3	2
371	2	1
372	1	6
373	5	4
374	4	3
375	3	2
376	2	1
377	1	6
378	5	4
379	4	3
380	3	2
381	2	1
382	1	6
383	5	4
384	4	3
385	3	2
386	2	1
387	1	6
388	5	4
389	4	3
390	3	2
391	2	1
392	1	6
393	5	4
394	4	3
395	3	2
396	2	1
397	1	6
398	5	4
399	4	3
400	3	2
401	2	1
402	1	6
403	5	4
404	4	3
405	3	2
406	2	1
407	1	6
408	5	4
409	4	3
410	3	2
411	2	1
412	1	6
413	5	4
414	4	3
415	3	2
416	2	1
417	1	6
418	5	4
419	4	3
420	3	2
421	2	1
422	1	6
423	5	4
424	4	3
425</td		

N6 IS A GYDE 6 + 42 + 20 3

5x3 array of Latin squares
of order 8

1	1	1	6	7	8	2	3	4	5	6	7	8	2	3	4	5	6	7	8
2	4	5	1	1	1	3	4	2	3	2	1	4	5	3	2	1	6	7	8
3	5	1	2	3	4	6	7	8	9	10	11	12	13	14	15	16	17	18	19
4	2	3	4	5	6	8	9	10	11	12	13	14	15	16	17	18	19	1	2
5	3	4	5	6	7	9	10	11	12	13	14	15	16	17	18	19	1	2	3
6	1	2	3	4	5	7	8	9	10	11	12	13	14	15	16	17	18	19	1
7	2	3	4	5	6	8	9	10	11	12	13	14	15	16	17	18	19	1	2
8	4	5	6	7	8	10	11	12	13	14	15	16	17	18	19	1	2	3	4
9	5	6	7	8	9	11	12	13	14	15	16	17	18	19	1	2	3	4	5
10	6	7	8	9	10	12	13	14	15	16	17	18	19	1	2	3	4	5	6
11	7	8	9	10	11	13	14	15	16	17	18	19	1	2	3	4	5	6	7
12	8	9	10	11	12	14	15	16	17	18	19	1	2	3	4	5	6	7	8
13	9	10	11	12	13	15	16	17	18	19	1	2	3	4	5	6	7	8	9
14	10	11	12	13	14	16	17	18	19	1	2	3	4	5	6	7	8	9	10
15	11	12	13	14	15	17	18	19	1	2	3	4	5	6	7	8	9	10	11
16	12	13	14	15	16	18	19	1	2	3	4	5	6	7	8	9	10	11	12
17	13	14	15	16	17	19	1	2	3	4	5	6	7	8	9	10	11	12	13
18	14	15	16	17	18	1	2	3	4	5	6	7	8	9	10	11	12	13	14
19	15	16	17	18	19	2	3	4	5	6	7	8	9	10	11	12	13	14	15

N6 IS A GYDE 6 + 28 + 14 3

3x1 array of
Latin squares
of order 8

4	6	5	3	7	8	2	1	9	10	11	12	13	14	15	16	17	18	19
5	4	6	2	7	3	8	9	10	11	12	13	14	15	16	17	18	19	1
6	8	7	2	3	4	5	6	7	8	9	10	11	12	13	14	15	16	17
7	2	3	8	4	5	6	7	8	9	10	11	12	13	14	15	16	17	18
8	2	3	4	5	6	7	8	9	10	11	12	13	14	15	16	17	18	19
9	7	4	5	6	8	9	10	11	12	13	14	15	16	17	18	19	1	2
10	4	5	6	7	8	9	10	11	12	13	14	15	16	17	18	19	1	2
11	4	5	6	7	8	9	10	11	12	13	14	15	16	17	18	19	1	2
12	3	4	5	6	7	8	9	10	11	12	13	14	15	16	17	18	19	1
13	3	4	5	6	7	8	9	10	11	12	13	14	15	16	17	18	19	1
14	3	4	5	6	7	8	9	10	11	12	13	14	15	16	17	18	19	1
15	3	4	5	6	7	8	9	10	11	12	13	14	15	16	17	18	19	1
16	3	4	5	6	7	8	9	10	11	12	13	14	15	16	17	18	19	1
17	3	4	5	6	7	8	9	10	11	12	13	14	15	16	17	18	19	1
18	3	4	5	6	7	8	9	10	11	12	13	14	15	16	17	18	19	1
19	3	4	5	6	7	8	9	10	11	12	13	14	15	16	17	18	19	1

N7 IS A GYDE 9 + 12 + 12 3

Latin square -
of order 9

1	2	3	4	5	6	7	8	9
4	5	6	1	3	2	8	9	7
6	4	2	1	7	8	5	3	9
2	1	3	7	8	6	4	5	9
5	3	6	4	1	2	9	7	8
7	8	9	5	4	6	3	2	1
9	7	8	6	5	4	3	2	1
1	2	3	4	5	6	7	8	9
3	2	1	6	7	8	9	5	4

N9 IS A GYDE (9 , 12 , 24)

3	5	7	1	6	8	2	4	9	1	5	9	2	6	7	3	4	8	4	5	6	7	8	9
1	2	3	4	5	6	7	8	9	3	5	7	1	6	8	2	4	9	7	8	9	1	2	3
1	5	9	2	6	7	3	4	8	1	2	3	4	5	6	7	8	9	1	2	3	4	5	6
3	5	7	1	6	8	2	4	9	1	5	9	2	6	7	3	4	8	4	5	6	7	8	9

N9 IS A GYDE (9 , 24 , 24)

4	2	6	9	8	1	5	3	7	5	2	4	1	8	7	9	6	2	4	3	5	6	7	8
3	4	2	9	7	5	1	8	6	4	3	5	2	9	7	8	6	4	3	5	2	9	7	8
5	6	3	1	8	7	9	6	4	2	3	5	7	8	9	6	4	2	3	5	7	8	9	6
6	7	8	3	2	1	9	5	4	6	7	8	1	9	5	4	6	7	8	3	2	1	9	5

2x2 array of Latin squares
of order 9

4	3	1	7	9	5	6	3	2	2	4	5	6	8	7	8	9	1	4	5	6	7	8	9
2	4	6	3	8	7	8	9	5	4	3	6	7	1	5	9	1	2	7	8	9	1	2	3
9	7	5	8	1	6	4	2	3	6	5	7	8	9	1	4	2	3	1	2	3	4	5	6
6	9	7	4	3	1	5	1	6	8	2	8	2	5	9	7	3	4	5	6	4	8	9	7
8	5	8	2	4	2	9	7	1	1	9	3	4	3	6	6	7	5	8	9	7	2	3	1
1	2	3	6	5	9	7	8	4	9	7	1	3	4	2	5	8	6	2	3	1	5	6	4

N10 IS A GYDE (10 , 15 , 36)

10	2	5	6	3	1	5	4	1	2	9	7	8	6	3	10	1	7	6	3	8	4	2	7
4	1	2	9	7	5	3	8	6	3	10	1	7	6	3	2	4	10	1	7	6	3	8	4
1	7	6	3	8	4	2	7	5	3	10	1	7	6	3	2	4	10	1	7	6	3	8	4
9	10	3	8	4	2	7	5	3	10	1	7	6	3	2	4	10	1	7	6	3	8	4	2

1x3 array of Latin squares
of order 10

5	10	9	4	9	5	6	10	4	3	1	7	3	2	8	6	6	5	1	3	8	7	2	1
7	8	2	9	5	10	1	2	3	9	4	1	6	10	5	10	2	8	3	6	7	4	8	9
6	1	3	3	4	4	2	7	10	1	9	5	8	3	10	2	7	1	9	8	5	8	10	6
8	9	4	10	2	2	7	8	8	5	6	3	1	5	6	5	4	3	10	1	10	7	2	4
4	5	6	7	8	6	10	9	1	2	10	4	2	7	3	1	3	9	7	2	6	5	3	10

N11 IS A GYD('10 , 45 , 18)

4x1 array of
Latin squares
of order 10

N12 IS A GYDE 12 + 44 + 33 3

7	11	10	6	0	4	12	1
6	3	11	10	12	8	9	1
4	12	9	11	1	7	10	2
0	1	10	12	2	5	11	3
6	2	11	1	1	9	12	4
12	3	10	2	4	1	7	5
11	4	1	8	3	5	2	6
2	6	5	12	9	4	3	7
10	5	4	3	7	1	6	8
1	5	2	4	0	3	12	9
3	5	12	4	7	2	6	10
1	7	4	5	6	3	8	11
2	8	5	2	9	6	4	12
5	8	6	9	10	7	3	1
4	10	7	0	6	11	9	2
5	9	8	10	12	11	7	3
6	10	6	1	11	12	9	4
7	12	9	11	2	10	1	5
9	3	12	5	2	1	11	6
9	4	1	11	5	3	2	7
10	2	5	6	12	4	3	8
11	6	3	1	7	4	5	9
10	7	2	4	5	6	8	10
12	7	4	5	6	2	8	10
3	1	11	2	9	6	5	11
2	9	6	8	4	10	7	12
3	8	7	9	11	5	10	1
4	10	11	9	8	6	12	2
5	11	7	2	10	8	6	3
6	9	8	2	10	12	1	4
7	1	9	2	11	8	10	5
8	12	2	10	3	9	11	6
9	11	3	12	1	10	4	7
10	4	12	1	5	11	2	8
11	2	1	6	3	12	5	9
12	6	2	3	4	7	1	10
1	2	3	4	5	2	8	11

6	3	4	5	10	7	8	9	12	11	12	1	2	3	4	5	6	7	8	9	10	11	12
7	4	8	6	2	11	12	3	10	1	2	3	4	5	6	7	8	9	10	11	12	1	2
11	7	10	9	12	3	9	4	1	6	2	3	8	5	6	7	11	12	1	2	3	4	5
8	9	12	11	7	2	4	10	2	5	7	6	9	8	11	10	12	3	1	5	3	4	6
4	10	5	12	1	8	6	1	0	12	9	7	4	9	10	11	2	3	11	10	1	4	2
10	11	11	1	6	1	2	5	3	4	8	7	12	1	0	12	9	3	12	1	10	5	4
12	3	2	3	4	5	3	7	5	8	7	10	9	12	1	1	11	12	1	2	6	3	12
11	2	3	4	5	3	7	5	8	6	10	11	12	1	2	4	9	6	7	8	9	10	1
1	1	2	3	4	5	6	7	8	9	10	11	12	1	2	3	4	5	6	7	8	9	10

N13 WOULD BE GYDE(15-35+21), BUT DOESN'T EXIST
SINCE FIF(15-35-6+14+5) DOESN'T EXIST.

N14 IS A GYDE 15 + 35 + 42 3

12	5	2	3	4	11	15	1	9	14	6	8
4	1	11	13	6	2	7	8	15	14	10	3
6	10	2	12	9	7	5	14	1	15	13	4
3	8	15	1	12	14	9	11	5	10	13	2
3	11	5	10	2	13	12	8	9	4	2	6
10	4	15	11	13	1	2	3	7	12	5	9
8	13	1	14	3	6	5	2	10	7	9	12
11	12	13	7	14	6	15	6	5	4	1	2
8	11	14	13	6	15	3	9	1	10	4	12
10	14	3	4	5	9	6	7	11	15	2	8
11	12	6	1	5	3	4	2	10	9	14	13
2	10	12	2	14	8	6	15	3	1	11	5
14	7	8	15	13	12	11	10	2	9	1	4
1	3	2	15	9	6	10	11	13	8	4	5
2	15	14	9	12	13	0	5	4	6	3	7
5	2	9	8	2	15	14	4	13	3	21	1
12	15	10	6	1	2	4	13	8	7	3	9
9	14	1	5	2	11	12	10	6	13	8	15
7	6	8	9	10	3	1	4	14	5	12	11
13	3	11	5	4	7	10	6	12	2	15	14
1	9	10	3	2	4	11	15	7	12	6	14
13	1	5	2	11	9	3	12	15	8	7	6
5	7	9	2	8	4	13	1	6	11	14	10
6	8	7	4	15	1	14	13	3	5	12	10
15	2	4	10	8	5	13	12	14	11	9	3
15	6	13	14	3	10	8	9	4	2	5	1
14	5	4	11	10	12	1	3	6	13	7	2
4	9	12	6	15	10	7	5	2	1	8	11
7	4	3	12	1	5	9	14	11	6	15	13
9	13	6	8	11	14	2	7	12	3	10	15

3	9	8	5	4	6	14	13	7	1	12	11	15	1	2	9	10	3	8	4	10	5	7	13	14	15					
2	1	5	12	3	15	4	9	8	10	13	9	11	7	6	4	7	14	10	2	1	8	5	3	14	13	12	11	15		
-5	4	1	2	6	10	9	8	12	11	10	3	8	15	5	13	12	9	6	14	11	13	14	7	4	3	12	1	4		
15	14	3	7	11	9	10	7	2	6	1	12	4	3	13	5	8	11	2	1	14	15	12	13	4	5	6	10	9	6	
10	2	13	4	1	5	8	3	6	2	4	5	2	14	14	12	11	15	15	13	3	9	1	11	12	8	7	6	10	9	11

MJS JS A GTE 16 • 20 • 20

1124 35 A GYPSI 21 • 30 , 35 ,

Latin square of order 21	2	4	6	12	8	3	10	15	16	17	11	20	14	21
	3	5	4	6	7	12	17	4	20	11	13	21	15	1
	20	7	5	0	9	10	21	18	2	12	19	16	13	11
	10	9	11	7	21	12	13	14	19	20	16	15	1	3
	17	16	4	10	3	11	7	6	13	15	21	1	5	9
	38	10	8	17	12	21	14	1	2	15	13	4	6	2
	9	21	14	11	18	15	19	2	3	6	1	5	13	7
	6	11	10	21	14	16	5	12	1	4	2	19	9	8
	7	1	12	15	13	17	11	16	8	2	25	4	20	6
	9	12	13	14	10	11	0	3	11	10	20	2	5	17
	12	2	15	18	15	14	1	20	4	3	4	2	9	10
	16	14	15	14	4	20	6	19	5	8	3	2	12	
	4	15	16	2	20	18	9	12	21	5	7	14	10	13
	15	10	17	6	19	6	20	16	21	2	9	13	14	1
	11	19	10	16	5	13	15	10	4	1	12	6	2	20
	21	17	12	1	20	2	19	3	5	15	2	10	12	5
	13	6	20	19	17	7	4	21	18	8	3	16	2	11
	19	20	21	3	1	9	16	4	12	13	14	18	11	12
	14	11	7	9	6	8	18	11	10	17	12	10	16	17
	5	3	2	1	11	4	12	13	14	16	15	19	17	18
	8	8	3	4	16	5	2	7	9	10	6	12	18	19

W37 15 A GTE 25 , 30 + 30 >

SHUFFLE

```
80 PRINT "FILE NAMES?"
90 INPUT A$,B$
100 FILE #1:A$
110 FILE #2:B$
115 MARGIN #2:0
120 DIM A(50,25),N(50,25),G(50)
130 INPUT #1:V,B,K
140 MAT A=ZER(B,K)
150 MAT N=ZER(B,K)
160 MAT INPUT #1:A(B,K)
170 LET M=INT(B/V)
180 FOR P=1 TO V
190     FOR J=1 TO K
200         FOR I=1 TO B
210             IF A(I,J)=P
220                 THEN LET A(I,J)=P+C*V
230                     LET N(P+C*V,J)=N(P+C*V,J)+1
240                     LET C =MOD(C+1,M)
250             CONTINUE
260         NEXT I
270     NEXT J
280     IF C>0
290         THEN PRINT "IMPROPER # OF TREATMENTS";P
300         LET Q=1
310     CONTINUE
320 NEXT P
330
332 LET M=1
334 PERFORM CHECK
336 DO WHILE M=1
338     PERFORM CHECK
340     FOR C=1 TO K
350         FOR R=1 TO B
360             IF N(R,C)=0
370                 THEN LET C1=1
380                     DO WHILE N(R,C1)<=1
390                         LET C1=C1+1
400                         IF C1>K THEN PRINT "HELP"
410                     LOOP
420                     MAT G=ZER(B)
430                     LET X=R
440                     PERFORM FINDY
450                     DO WHILE N(Y,C)=1 AND N(Y,C1)>0
460                         PERFORM EXCHANGE
470                         LET X=Y
480                         PERFORM FINDY
490                     LOOP
500                     PERFORM EXCHANGE
510             CONTINUE
520         NEXT R
530     NEXT C
535 LOOP
```

```
540 IF Q=0
545     PERFORM UNSCRAMBLE
550 THEN
570     SCRATCH #2
575     PRINT #2:V$,";B$,";K
580     FOR I=1 TO B
590         FOR J=1 TO K
600             PRINT #2:A(I,J)$,";
610         NEXT J
620         PRINT #2:
630     NEXT I
640 ELSE PRINT "NO WRITING DONE IN FILE";B$
650 CONTINUE
670
680 DEFINE FINDY
690     LET I=1
700     DO WHILE A(I,C1)<>X OR G(I)=1
710         LET I=I+1
720         IF I>B THEN PRINT "HELP"
730     LOOP
740     LET Y=A(I,C)
750     LET G(I)=1
760 DEFEND
770
780 DEFINE EXCHANGE
790     LET A(I,C)=X
800     LET A(I,C1)=Y
810     LET N(X,C)=N(X,C)+1
820     LET N(X,C1)=N(X,C1)-1
830     LET N(Y,C)=N(Y,C)-1
840     LET N(Y,C1)=N(Y,C1)+1
850 DEFEND
855
860 DEFINE CHECK
862     REM: RETURNS M=1 IF MATRIX NOT RIGHT
865     LET M=0
870     FOR C=1 TO K
880         FOR R=1 TO B
890             IF N(R,C)<>1 THEN LET M=1
900         NEXT R
910     NEXT C
920 DEFEND
925
930 DEFINE UNSCRAMBLE
932 FOR J=1 TO K
934     FOR I=1 TO B
936         LET A(I,J)=MOD(A(I,J)-1,V)+1
938     NEXT I
940 NEXT J
942 DEFEND
1000 END
READY
```

References

1. Agrawal, H. (1966). Some generalizations of distinct representatives with applications to statistical designs. Ann. Math. Statist. 37 525-528.
2. Cheng, C.-S. (1978). Optimality and Construction of Pseudo Youden Designs. Technical Report, Univ. of California, Berkeley, CA.
3. Collens, R. J. (1976). Constructing BIBD's with a computer. Ars Combinatoria 2 285-303.
4. Hanani, H. (1975). Balanced incomplete block designs and related designs. Discrete Math. 11 255-369.
5. Kiefer, J. (1975). Balanced block designs and generalized Youden designs, I. Construction (patchwork). Ann. Statist. 3 109-118.
6. Kiefer, J. (1975a). Construction and Optimality of Generalized Youden Designs. In A Survey of Statistical Design and Linear Models (J. N. Srivastava, ed.) 333-353. North-Holland, Amsterdam.
7. Ruiz, F. and Seiden, E. (1974). On construction of some families of generalized Youden designs. Ann. Statist. 2 503-519.
8. Seiden, E. and Wu, C. Y. (1978). A geometric construction of generalized Youden designs for v a power of a prime. Ann. Statist. 6 452-460.

Generalized Youden Designs are generalizations of the class of two-way balanced block designs which include Latin squares and Youden squares. They are used for the same purposes and in the same way that these classical designs are used, and satisfy most of the most common criteria of design optimality.

We explicitly display or give detailed instructions for constructing all these designs within a practical range: when v , the number of treatments, is ≤ 25 ; and b_1 and b_2 , the dimensions of the design array, are each ≤ 50 .

\leq or =